

## Two wire current Hall switch sensor

### 1. Product Introduction

HK542 is a Hall switch chip designed based on BCDMOS technology. The sensors includes hall devices with temperature compensation, dynamic offset cancellation amplifiers, comparators, and output stages. The chip outputs current. The comparator compares the actual magnetic flux with a fixed reference value (switching point) to control the current level of the output MOSFET. Active offset compensation can generate magnetic characteristics with specific temperature coefficients under various power supply voltages. In addition, mechanical stress has little effect on magnetic parameters. In addition, mechanical stress has little effect on the magnetic parameters of the chip.

The series of chip sensors is suitable for industrial and automotive applications, with an ambient temperature range of -40 °C to 150 °C and supply voltage range of 3.0V to 30V. AH542 provides a variety of packages to customers:TO92S、SOT23 (small)、SOT23. All packages are RoHS compliant. The product has passed AEC-Q100 certification.



### 2. Function

- AEC-Q100 Grade 0 Automotive Level Certification
- Operating Vcc Range:3.0V~30V
- ESD: ±12kV
- High mechanical stress suppression ability
- Switching points with specific temperature coefficients
- Temperature range: -40°C~150°C
- Reverse-voltage protection at Vcc pin
- Suitable for automobiles and industries

### 3. Application

- Speed and RPM sensing
- Tachometer sensor、Flow-rate sensing
- DC motor, fan control, robotics control
- Proximity sensor、Position sensor
- Seat belt buckles、hood/trunk/door latches
- Sunroof/convertible top/tailgate
- Liftgate activation
- Brake/clutch pedals
- Electric power steering(EPS)
- Transmission shifting
- Wiper motor

## Two wire current Hall switch sensor

### 4. Products packaging


Part No.	Packages	temperature range	Packing
HK542UA	T092S	-40°C~150°C	1000pcs/bag
HK542SU	SOT23-3L	-40°C~150°C	3000pcs/reel
HK542SS	SOT23 (small)	-40°C~150°C	3000pcs/reel

**Two wire current Hall switch sensor****Table of Contents**

1. Product Introduction .....	1
2. Function .....	1
3. Application.....	1
4. Products packaging .....	2
5. Functional Block Diagram.....	4
6. Pin information .....	4
7. Absolute Maximum Ratings .....	5
8. Recommended operating conditions.....	5
9. Electrical Parameters .....	6
10. Magnetic Parameters.....	6
11. Magnetic Characteristics.....	6
12. Typical Application Circuit.....	7
13. Characteristic Performance .....	8
14. Package Material Information.....	9
15. Note.....	12
16. Historical Version.....	12



## Two wire current Hall switch sensor

### 5. Functional Block Diagram



### 6. Pin information

No.	Name	Functions
1	VCC	Power supply voltage 2.7V~30V
2	GND	Ground wire
3	VOUT	NC ( undefined )



T092S

SOT23 (small) / SOT23-3L

## Two wire current Hall switch sensor

### 7. Absolute Maximum Ratings

Absolute maximum ratings are limited values to be applied chips, and beyond which the absolute maximum rating may damage chips. Although the functionality is not necessarily damaged, exposure to absolute maximum rating conditions for an extended period of time may affect device reliability

Symbol	Parameters	Pins	Min	Max	Unit	Test condition
V <sub>CC</sub>	supply voltage	1	-20	30	V	t<1000h <sup>1)</sup>
			-	34	V	t<96h <sup>1)</sup>
			-	36	V	t<5min <sup>1)</sup>
T <sub>A</sub>	operating ambient temperature		-40	170	°C	
T <sub>s</sub>	storage temperature		-65	170	°C	-
T <sub>J</sub>	maximum junction temperature			165	°C	-

<sup>1)</sup> No accumulated stress

### 8. Recommended operating conditions

When the operation of the chip exceeds the range described in the recommended operating conditions, it may lead to abnormal chip operation and may reduce reliability and service life

Symbol	Parameters	Pins	Min	Typ	Max	Unit
V <sub>cc</sub>	supply voltage	1	3.0	-	30	V
T <sub>A</sub>	operating ambient temperature	-	-40	-	150	°C

### ESD ratings

Symbol	Describe	Executive standards	Max	Unit
V <sub>ESD</sub>	HBM	JEDEC JS-001-2017	12	kV

## Two wire current Hall switch sensor

### 9.Electrical Parameters


Test conditions:  $V_{CC}=3.0V\sim30V$ ,  $T_A=-40^{\circ}C\sim150^{\circ}C$

Symbol	Parameters	Pins	Min	Typ	Max	Unit	Test condition
$I_{VCC\_LO}$	Power supply low current	1	4.0	6.0	8.0	mA	$B>B_{Rp}$ ire
$I_{VCC\_HI}$	Power supply high current	1	12	15	18	mA	$B<B_{op}$
$I_{CCR}$	reverse current				1	mA	$V_{cc}=-18V$
$B_{NOISE}$	Effective noise of switching points			1		Gs	Suitable for square wave signals of 1kHz

### 10.Magnetic Parameters

Part No.	Switch Type	TC (pp m/K)	Bop (Gs)			Brp (Gs)			B <sub>HYS</sub> (Gs)		
			Min	Typ	Max	Min	Typ	Max	Min	Typ	Max
HK542	Bipolar	0	-	121	-	-	-121	-	-	242	-

### 11.Magnetic Characteristics




## Two wire current Hall switch sensor

### 12.Typical Application Circuit

The following figure shows a simple application with a 2-wire sensor. Current consumption can be detected by measuring the voltage on the  $R_L$ . In order for the sensor to function properly, the voltage between  $V_{CC}$  and GND must be at least  $V_{CCMIN}$ . At maximum current consumption of  $I_{CC\_HIMAX}$ , the maximum  $R_L$  can be calculated as:


$$R_{Lmax} = \frac{V_{BATTmin} - V_{ccmin}}{I_{CCHimax}}$$







Typical Application Circuit 1

For applications with interference or radiation interference on the power line, it is recommended to place a series resistor  $R_V$  and a capacitor  $C_P$  near the sensor. In this case, the maximum  $R_L$  can be calculated as:

$$R_{Lmax} = \frac{V_{BATTmin} - V_{ccmin}}{I_{CCHimax}} - R_V$$




Typical Application Circuit 2

**Two wire current Hall switch sensor****13.Characteristic Performance**V<sub>cc</sub>=5V, Bop and Brp Characteristic PerformanceV<sub>cc</sub>=5V, Supply current Characteristic PerformanceV<sub>cc</sub>=3.0~30V, Average power supply current (low) Characteristic PerformanceV<sub>cc</sub>=3.0~30V, Average power supply current (low) Characteristic Performance

## Two wire current Hall switch sensor

### 14.Package Material Information


#### TO92S Package Size



Symbol	Dimensions in Millimeters		Dimensions in Inches	
	Min	Max	Min	Max
A	1.420	1.620	0.056	0.064
A1	0.770TYP			0.030TYP
b	2.440	2.650	0.096	0.104
b1	2.580TYP			0.102TYP
D	3.900	4.100	0.154	0.162
E	2.900	3.100	0.114	0.122
e	1.270TYP			0.050TYP
e1	2.540TYP			0.100TYP
L	15.500	16.200	0.610	0.638
θ	45°TYP			45°TYP

## Two wire current Hall switch sensor


### SOT23-3L Package Size



Symbol	Dimensions in Millimeters		Dimensions in Inches	
	Min	Max	Min	Max
A	1.050	1.300	0.041	0.051
A1	0.000	0.150	0.000	0.006
A2	1.000	1.200	0.039	0.047
b	0.300	0.500	0.012	0.020
c	0.080	0.220	0.003	0.009
D	2.800	3.020	0.110	0.119
E	1.500	1.700	0.059	0.067
E1	2.600	3.000	0.102	0.118
e	0.950TYP		0.037TYP	
e1	1.800	2.000	0.071	0.079
L	0.300	0.600	0.012	0.024
x	1.460TYP		0.057TYP	
y	0.800TYP		0.032TYP	
z	0.600TYP		0.024TYP	
θ	0°	8°	0°	8°

## Two wire current Hall switch sensor

### SOT23 (small) Package Size



Symbol	Dimensions in Millimeters		Dimensions in Inches	
	Min	Max	Min	Max
A	0.900	1.150	0.035	0.045
A1	0.000	0.100	0.000	0.004
A2	0.900	1.100	0.035	0.043
b	0.300	0.500	0.012	0.020
c	0.132	0.202	0.005	0.008
D	2.800	3.000	0.110	0.118
E	1.200	1.400	0.047	0.055
E1	2.250	2.550	0.089	0.100
e	0.950TYP		0.037TYP	
e1	1.800	2.000	0.071	0.079
L	0.300	0.500	0.012	0.020
x	1.460TYP		0.057TYP	
y	0.650TYP		0.026TYP	
z	0.500TYP		0.020TYP	
θ	0°	8°	0°	8°

## Two wire current Hall switch sensor

---

### 15. Note

- Hall chips are sensitive devices, and electrostatic protection measures should be taken during use, installation, and storage.
- During installation and use, mechanical stress applied to the device casing and leads should be minimized as much as possible.
- It is recommended that the welding temperature should not exceed 350 °C and the duration should not exceed 5 seconds.
- To ensure the safety and stability of Hall chips, it is not recommended to use them beyond the parameter range for a long time.

### 16. Historical Version

No.	Time	Describe
1	September 6th, 2022	Update Characteristic Performance。
2	December 22th, 2022	Update static voltage output error range
3	February 9th, 2023	Update IC limit of operate temperature and storage temperature
4	April 19th, 2023	Version update to V1.2